




ENERGY SAVING REPLACEMENTS FOR FLUORESCENT T8. Every size and installation method you need — in the highest quality, best light output design.


- Hybrid driver allows installation w/ compatible instant start ballasts* or 120-277VAC line voltage
- Install as single or double-ended power
- 10W, 11W, 12W, & 15W models available
- Available in 2 FT, 3 FT, & 4 FT
- Frosted glass allows for uniform illumination and softer light output
- Approved for open and enclosed fixtures

FLEXCOLOR
SWITCH BETWEEN 5 CCTs


OPTIONAL EMERGENCY BATTERY BACKUP




LED-EMG-05WCP / LED-EMG-10WCP
(SEE EMERGENCY DRIVER SPEC SHEET FOR ORDERING AND MORE INFO)



LED-10T8-FCAB24-G4



LED-11T8-FCAB36-G4



LED-12T8-FCAB48-G4 / LED-15T8-FCAB48-G4



GLASS CONSTRUCTION



CRI



LIGHT DISTRIBUTION



BALLAST BYPASS OR COMPATIBLE ELECTRONIC BALLAST*



SINGLE OR DOUBLE-ENDED



-40°F TO 104°F



BEAM ANGLE



50,000hrs RATED LIFE

PART #	UPC	REPLACES	WATTAGE	LUMENS	CCT	BASE	DLC CODE
LED-10T8-FCAB24-G4	197810005988	17W	10W	1450	FLEXCOLOR 3000K/3500K/ 4000K/5000K/ 6500K	G13	S-7MG7GF
LED-11T8-FCAB36-G4	197810005995	25W	11W	1650			S-RDX5L5
LED-12T8-FCAB48-G4	197810006008	32W	12W	1800			S-6GRHYK
LED-15T8-FCAB48-G4	197810006015		15W	2200			S-J0PGVS

* LAMP IS COMPATIBLE WITH CERTAIN INSTANT START BALLASTS. PLEASE VERIFY COMPATIBILITY PRIOR TO INSTALLATION.

DEFAULT CCT IS SHOWN IN BOLD

