



Product Family Name:  
Item Number: 770637  
Ordering Code: LED675/30K/S/D  
Item Number:  
Ordering Code:

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	iLumaTech	IP06	Bad	1	Flicker at LE-Med-HI
		SureSlide	6633-P	Good	1	Dims down to 1%, flicker at 80%
	Lutron	Vizia	VPI06-1LZ	Good	1	Dims down to 1%, flicker at LE
		Toggle	TG-600	Bad	1	Flicker at 5%-100%
		Divi	DV-600	Bad	1	Flicker at 30%-100%
		SkyLark	S-600	Best	1	Dims down to 1%
	Legrand	Maestro	MAW-600	N/A	1	Can't turn on & off the lamp.
		Titan	CD703-PW	Bad	1	Flicker at 20%-30%
		Harmony	D703-PTC	Good	1	Dims down to 1%, flicker at 15%
		Harmony	H703-PTC	Bad	1	Flicker at LE-Med-HI
CFL/LED	Leviton	iLumaTech	IPL06	Best	1	Dims down to 1%
		SureSlide	6674	Best	1	Dims down to 1%
	Lutron	Decora	6672	Best	1	Dims down to 1%
		SkyLark	CTCL-153	Bad	1	Flicker at 20%-90%
		Divi	DVCL-153P	Best	1	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	Dims down to 1%
		SkyLark	SCL-153P	Best	1	Dims down to 1%
		Toggle	TGCL-153PH	Best	1	Dims down to 1%
		Radio RA	RA2R-6CL-PD	Best	1	Dims down to 1%
		Harmony	DCL453-PTC	Best	1	Dims down to 1%
Legrand	Harmony	HCL453PTC	Best	1	Dims down to 1%	
	Adorne Paddle	ADP453LM2	Bad	1	Flicker at 10%-90%	
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	Dims down to 1%
		iLumaTech	IPED4	Best	1	Dims down to 1%
	Lutron	Decora	6615-P	Best	1	Dims down to 1%
		SkyLark Countour	CTELV-303P	Best	1	Dims down to 1%
		Divi	DVELV-300P	Best	1	Dims down to 1%
		Maestro	MAELV-600	Best	1	Dims down to 1%
		SkyLark	SELVB-300P	Best	1	Dims down to 1%
		VIERI	VTEL-600M-W	Best	1	Dims down to 1%
		Scene Director	SCELL	Best	1	Dims down to 3%
		Magentic Low Voltage	Leviton	Vizia	YPM-06	N/A
Decora	6613-P		Good	1	Dims down to 1%, flicker at 10%	
Maestro	MALV-600		N/A	1	Can't turn on & off	
Legrand	Harmony	DLV703-PW	Best	1	Dims down to 1%	
	Titan	CDLV703-PW	Best	1	Dims down to 1%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-8LZ	Best	1	Dims down to 2%
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A		
	Insteon	SwitchLin Remote Control dimmer		N/A		
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	Dims down to 1%, shimmer at LE
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A		
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A		
Universal	Legrand	gt	ZW3005	Best	1	Dims down to 1%
		Adorne SoftTap	ADTP703TU	Best	1	Dims down to 5%
		Miro Decorator	DRD4-W	Good	1	Dims down to 1%
		Harmony	H703PTUTC	Best	1	Dims down to 6%
	Cooper	Adorne Whisper	ADWH700RMTUW2	Best	1	Dims down to 1%
		Adorne Touch	ADTH700RMTUM2	Best	1	Dims down to 1%
Decorator	DAL06P-C2-K-L	Good	1	Dims down to 6%, flicker at 6%		
Skye	SAL06P-W-K-L	Good	1	Dims down to 5%, flicker at 7%		

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturers.  
 †May experience "pop-on"; lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering; minimal audible noise (typically less than 25 dba); wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	